


SX-590 ファームウェアのアップデート手順

本紙では、SX-590(以降、本製品)のファームウェアアップデート手順について記載しています。

1. 本製品の内蔵 Web ページを開きます。
※内蔵 Web ページを開くには、Web ブラウザを起動してアドレスバーに本製品の IP アドレスを入力して、Enter キーを押下します。AMC Manager®(本製品の統合管理ソフトウェア)から設定する本製品を選択して「」アイコンをクリックすることでも Web ページにアクセスできます。
2. 本製品の Web ページにアクセスするとシステムステータスページが表示されます。左側のメニューから「**ログイン**」をクリックします。

注意:

本製品にパスワードが設定されていない場合は、パスワード設定ページが表示されます。

3. パスワードを入力して「**ログイン**」ボタンをクリックします。
4. システムステータスページに戻ります。左側のメニューに新しい項目が追加されます。Web ページ左側の設定メニューから「**ファームアップデート**」をクリックして「**ファームアップデート**」ページを表示します。「**参照**」ボタンをクリックして、ダウンロードしたファームウェア (SX-590.bin) を指定します。
5. 「**新しいファームウェア**」フィールドに正しいファイル名が表示されていることを確認して「**アップデート**」をクリックします。
6. アップデート確認画面で「**OK**」をクリックすると、ファームウェアのアップデートが開始されます。ファームウェアのアップデートが完了するまで、しばらくお待ちください。

注意:

ファームウェアのアップデート中は、本製品の電源を切ったり、Web ブラウザを終了したりしないでください。

7. ファームウェアのアップデートを行った本製品のシステムステータスページが表示されたら、ファームウェアのアップデートは完了です。Web ページの左下に表示されているバージョン表記を確認して、ファームウェアが最新バージョンに更新されていることを確認してください。

サイレックス・テクノロジー株式会社


URL: www.silex.jp

【 製品に関するお問合せ 】

E-mail: support@silex.jp

SX-590 Firmware Update Procedure

This document describes how to update the firmware of SX-590.

1. Access the internal Web page of SX-590. To access the internal Web page, open your Web browser and enter the IP address of SX-590 into the address bar and press Enter key.
(* The Web page can also be accessed using the AMC Manager® (total management utility for SX-590). Start the AMC Manager® and select SX-590 that you wish to update the firmware and clicking the icon . The internal Web page will be displayed.)
2. When you have connected to the SX-590, you will get the **System Status** page. Click **Login** on the left side of the screen.

NOTE:

When the password is not configured to SX-590, the *Password Configuration* page is displayed.

3. Enter the password for the unit and click **Login**.
4. You will return to the **System Status** page, but new options will be listed on the left side of the screen. In the Web page, click **Firmware Update** on the left menu. In the **Firmware Update** page, click **Browse** to specify the firmware update file that you have downloaded into your computer (SX-590.bin file).
5. Check the correct file name is displayed in **New firmware** field and click **Update**.
6. The update confirmation message is displayed. Click **OK** to begin the firmware upgrade.

NOTE:

Do not turn off SX-590 or close your Web browser while the firmware upgrade is in process.

7. When the **System Status** page is displayed, the firmware update is completed. See the bottom left of the page and check the version information is changed.

Silex Technology America, Inc.

<https://www.silextechnology.com/>

Technical Support: support@silexamerica.com

Sales: sales@silexamerica.com

Silex Technology Europe GmbH

<https://www.silextechnology.com/>

Email: contact@silexeurope.com